Call Rejection

Control your phone by blocking unwanted or annoying calls. Call Rejection lets you store up to 15 different numbers on your "Rejection List." When an unwanted caller tries to get through, a pre-recorded message says you're not accepting calls.

To activate



To cancel



Follow the recorded instructions to enter the phone numbers of callers you want to reject. Not all long-distance or wireless calls can be rejected.

Please refer to the back for more detailed instructions.



How to use Call Rejection

- To block unwanted calls, lift the receiver, press *60 and follow the recorded instructions to enter the phone numbers of unwanted callers.
- When an unwanted caller tries to call you, a standard CenturyLink recorded message says that you are not accepting calls.
- If you don't know the caller's number, you can activate Call Rejection immediately after you get a call from that person. Just hang up, then lift the receiver again, press *60 and follow the recorded instructions.
- Up to 15 numbers can be stored on your unwanted callers list. This
 feature works with most local and some long-distance numbers within
 your area.
- To temporarily deactivate Call Rejection, press *80.

For Rotary Phones

If you are using a rotary-dial telephone instead of a touch-tone phone, dial 1 in place of the * key. For example * **60** is 1 **60** on rotary phones.

Available in most areas. Some restrictions apply.

©2011 CenturyLink, Inc. All Rights Reserved. CRJ C 8/11